



FOR SEQUENCE OF MULTIPLES & WIRING OF OUTLETS SEE EXT LINE CCT GBW 13210 OR EQUIV

FOR WIRING OF OUTLETS SEE MARKER CCT GBW 13230 OR EQUIV

FOR SEQUENCE OF MULTIPLES & WIRING OF OUTLETS SEE EXT LINE CCT GBW 13210 OR EQUIV

FOR WIRING OF THESE LEADS SEE PULSE CCT GBW 13260 OR EQUIV

EXCH LINE ST ETH FROM PULSE CCT FOR WIRING OF THESE LEADS SEE PULSE CCT GBW 13260 OR EQUIV

FROM EB TAG ON BANK MULTI STRIP CONN GBW 13210 OR EQUIV (1st EXCH LINE CCT ONLY) OR FROM UIS OF PRECEDING EXCH LINE CCT

TO UIS OF NEXT EXCH LINE CCT (ODD CCTS R-G) (EVEN R-O) UIS OF LAST CCT TO BE STRAPPED TO U11

FROM MISC CCTS GBW 13270 FIG 3 OR EQUIV

FROM MARKER CCT GBW 13230 OR EQUIV

FROM MISC CCTS GBW 13270 FIG 3 OR EQUIV

SK FROM ATT'S CABINET GBW 13240 OR EQUIV

FROM MARKER CCT GBW 13230 OR EQUIV

FROM MISC CCTS GBW 13270 FIG 3 OR EQUIV

FROM ATT'S CABINET GBW 13240 OR EQUIV

NSK FROM MISC CCT GBW 13270 FIG 3 OR EQUIV

BATT BK FUSE U12-EF_a
 BATT W U12-MHC-MHE-MFE-CR_e-ST_e-M_e He ER_e-BR_b BR_e-CL_b CL_e-B_e-A7 DR_e-G_e-R₆b-R7_b-R₈b

EARTH R ETH BAR U11-EF_t1
 EARTH R U11-TR_e-MH-LB3-AC21-AC4-CR24-EB1-SB23-SB28-M26-H25 H26 H5 ET1-ET4 ER21-B21-L54-DR_b-R5_b-R₁b

- NOTES**
- FUSE 1 5A PER CIRCUIT
 - SHLEF JACK POINTS 9, 11, U13-U15 U17-U19, U76-U78 U79-U81 & U80-U82 MAKE CONTACT WHEN RELAY SET IS REMOVED
 - RELAY DR IS DIFFERENTIALLY CONNECTED & IS OPERATED BY AN EARTH APPLIED TO THE +VE LEAD FROM THE SUBSET ENQUIRY PUSH BUTTON
 - EARTH ON 'A' LEAD OF MAIN EXCH LINE CCT TO BE PERMANENTLY DISCONNECTED
 - 25-POINT UNISELECTORS ON 5+80 EQUIPMENTS
 50- " 7+35 & 10+49 EQUIPMENTS
 - Ø FOR ROUTING SEE GBW 13280 OR GBW 13300 OR EQUIV
 - ALL WIRING BEARING A COLOUR CODE TO BE 0.6mm UNLESS OTHERWISE SPECIFIED RELAY SET & UNISELECTOR BANK WIRING TO BE 0.5mm
 - CONNECTION U76 TO U6 OF ENQUIRY CIRCUIT WIRED ONLY ON 1st EXCH LINE CCT U76 OF SUBSEQUENT CIRCUITS WIRED TO U76 OF PRECEDING CCT U76 OF EVEN CCTS WIRED IN R-S, ODD CCTS IN R-O
 - STRAP U59-U61 FOR MAIN EXCHANGES WITH BATTERY RINGING OR RING RETURN CONNECTED TO 'A' LEG IN ADDITION WHEN CONNECTED TO CHICAGO STROMBERG OR ROTARY 7A AND 7A1 EXCHANGES PROVIDE A 200 OHM RESISTOR BETWEEN CONTACTS CR33 (SPRINGSET CR6) AND CA5 (SPRINGSET CA2)
 - STRAP U56-U58 IF PABX EXTENSION IS PERMITTED TO FLASH THE MAIN EXCHANGE OPERATOR
 - STRAP U61-U63 FOR MAIN EXCHANGES WITH EARTHED RINGING OR RING RETURN CONNECTED TO 'A' LEG

SUPERSEDED BY GBW 14-690

RETRACED & INCORPORATED		(157600)		G.A. 3 9 78 P.J.M.	
NOTE 10 & REF THERE TO REINSTITUTED		5079		28/12/57 G.F.F.	
AMENDMENT PARTICULARS		ISSUE DATE		APP ^d	
TZPO		DRAWN S.H.B.		CHECKED WIRING CIRCUIT R.H.A.	
GBW 13220					